

INFO vedr. håndholdt Programmer CBC000-AF08-01

CBC000-AF08-01 (den blå) er en håndholdt programmerings enhed til programmering af de 2 mulige hastigheder: High and low.

W1G200/ ESM produkterne, er pre-programmerede med 2 hastigheder. Disse er oplyst på det specifikke datablad.

Der er flere generationer af ESM7W1G200 produkter i omløb. De "gl" er begrænsede i RPM området.

De nyeste produkter, kan programmeres ned til 300 rpm.

Module 60697 (older generation) – 700 U/min

Module 61331 (latest generation) – 300 U/min

Dette Modul versions nummer, kan aflæses i WEB-PDM og/eller i de detaljerede data i Business1.


CBC000-AF08-01

Operating instructions

Programming unit for ESM range

5.1.2 Connecting the unit

1. Insert the RJ45 connector in the matching socket.
The connection for the RJ45 connector is located on the end face of the programming unit.
2. Make sure the connector is heard to engage.



values of the current option.

6.1.2 Programming options

CHANGE SPEED 1

"SPEED 1" is the speed at which the fan runs when the control line (brown wire) is not connected.

If this option is chosen with the "Select" button, the currently programmed speed is displayed (speed in rpm).

This speed can be varied in steps of 10 rpm - down to a minimum speed of 700 rpm.

In the case of fans with an extended range of functions (*ESM+), the minimum speed can be reduced to 300 rpm. Speeds below 300 rpm cannot be entered; this would cause the programming unit to switch to the "0 rpm" (standby) setting in the next step.

NB!!! Programmeren skal også være opgraderet til seneste version. Se Software opdaterings vejledning:

Nyeste Software kan findes og downloades fra vores US kollegers hjemmeside:

http://catalog.ebmpapst.us/downloads/esm_programmer.asp?_ga=2.236009479.765669422.1521638805-423773529.1511428247

Under support, digitale downloads.

Med venlig hilsen/Best regards

Henrik Dahl Thomsen

Product Manager